

SUPPLEMENTARY DATA - WESTERN ELECTRIC TUBES

TUBE	FIL	SELECTORS	BIAS VOLTS	SHUNT	PRESS	MMHOS RANGE	AVER. MUT. COND.	NOTATIONS
101D	4.3	ER-3200-0	7.5	---	P4	E	1070	Short on A
101F, J, L, M	4.3	ER-3200-0	10.0	---	P4	E	1120	Short on A
101F, A	4.3	ER-3200-0	11.0	---	P4	E	1400	Short on A
102D, F, L	2.0	ER-3200-0	2.6	---	P4	E	510	Short on A
104D	4.3	ER-3200-0	24.0	---	P4	E	1180	Short on A
205D E, F	5.0	ER-3200-0	4.0	---	P4	E	1500	Short on A
231D	3.0	ER-3200-0	12.0	---	P4	E	510	Short on A
244A	2.0	FR-3204-0	5.5	---	P4	E	1000	
245A	2.0	FR-0234-0	2.4	---	---	E	750	CAP=G Hold down P1 and Press P4
247A	2.0	FR-3204-0	5.3	---	P4	E	940	
257A	3.0	ER-0200-0	12.0	---	P4	E	510	CAP=G Short on A
259A, B	2.0	FR-0234-0	0.8	---	---	D	1380	CAP=G Hold down P1 and Press P4
262A, B	10.0	ER-0203-0	3.8	---	P4	E	900	CAP=G
271A	5.0	FR-3204-0	4.5	---	P4	D	2920	
272A	10.0	FR-3204-0	15.5	---	P4	E	760	
274A	5.0	ER-0300-0	0.0	77	P3	G	☆	Plate No. 1 Short on A
274A	5.0	ER-0200-0	0.0	77	P3	G	☆	Plate No. 2 Short on A
274B	5.0	JS-0600-0	0.0	77	P3	G	☆	Plate No. 1 Short on A
274B	5.0	JS-0400-0	0.0	77	P3	G	☆	Plate No. 2 Short on A
275A	5.0	ER-3200-0	30.0	---	P4	D	2500	
283A	2.0	FR-0234-0	0.6	---	---	D	1360	CAP=G Hold down P1 and Press P4
285A	2.0	FR-0234-0	8.5	---	P4	E	880	CAP=G
286A	2.0	GR-0235-4	5.0	---	P4	D	1000	CAP=G
290A	10.0	GR-0235-4	4.0	---	P4	E	1220	CAP=G
291A	10.0	HR-0236-5	0.5	---	---	D	2000	Ampl. Sect. CAP= G Hold down P1 and Press P4
291A	10.0	HR-5436-2	17.0	---	P4	D	500	Osc. Sect.
292A	10.0	GR-0205-0	7.0	---	P4	D	750	Triode Sect. CAP=G
292A	10.0	GR-0405-2	0.0	---	P1	C	☆	Diode No. 1
292A	10.0	GR-0305-2	0.0	---	P1	C	☆	Diode No. 2
293A	10.0	GR-4235-0	10.0	---	P4	E	1050	
294A	10.0	FR-0234-0	10.0	---	P4	E	1050	CAP=G

300A, B	5.0	ER-3200-0	14.0	---	P4	D	4000	Short on A
303A	2.0	GR-0205-0	7.0	---	P4	D	750	Triode Sect. CAP=G
303A	2.0	GR-0405-2	0.0	---	P1	C	☆	Diode No. 1
303A	2.0	GR-0305-2	0.0	---	P1	C	☆	Diode No. 2
309A	10.0	FR-0234-0	0.5	---	---	D	1100	CAP=G Hold down P1 and Press P4
310A, B	10.0	GR-0235-4	2.5	---	P4	D	1800	CAP=G
311A, B	10.0	FR-0234-0	7.5	---	P4	D	2800	CAP=G
313C	OFF	AP-0201-4	0.0	50	P5	G	☆	Short on 2, 3, 4, 5
328A	7.5	GR-0235-4	2.5	---	P4	D	1800	CAP=G
329A	7.5	FR-0234-0	7.5	---	P4	D	2800	CAP=G
336A	10.0	GR-4235-0	1.2	---	P4	D	4000	
337A	10.0	GR-0235-4	2.6	---	P4	D	1650	CAP=G
339A	5.0	BV-3020-4	3.0	---	P4	D	3500	CAP=P Short on A
347A	6.3	HS-0408-0	5.0	---	P4	E	900	CAP=G
348A	6.3	HS-0348-5	2.4	---	P4	D	1800	CAP=G
349A	6.3	HS-5348-0	1.2	---	P4	D	4000	
350A	6.3	FR-3024-0	3.0	---	P4	C	6000	CAP=P
350B	6.3	HS-5348-0	3.0	---	P4	C	6000	
351A	6.3	HS-0308-0	0.0	86	P3	G	☆	Plate No. 1
351A	6.3	HS-0508-0	0.0	86	P3	G	☆	Plate No. 2
352A	10.0	GR-0205-0	6.0	---	P4	D	750	Triode Sect. CAP=G
352A	10.0	GR-0405-0	0.0	---	P1	C	☆	Diode No. 1
352A	10.0	GR-0305-0	0.0	---	P1	C	☆	Diode No. 2
367A	6.3	HV-6248-0	3.7	---	P4	C	5500	
373A	2.0	HS-4860-3	1.6	---	P4	D	1320	Short on A
374A	3.0	HS-4860-3	6.0	---	P4	D	3100	Short on A
375A	20.0	HS-5348-0	7.0	---	---	D	4700	Hold down P1 and Press P4
381A	6.3	JS-0501-0	0.0	---	P1	E	☆	Diode
383A	6.3	JS-4601-0	3.6	---	P4	D	2800	
385A	6.3	JS-5031-7	1.9	---	P4	D	2500	CAP=P
387A	6.3	JS-5031-7	1.3	---	P4	D	4000	CAP=P
396A/2C51	6.3	KR-7608-2	2.0	---	P4	C	3150	Triode No. 1
396A/2C51	6.3	KR-3402-8	2.0	---	P4	C	3150	Triode No. 2
398A/5603	6.3	CX-4860-3	1.0	---	P4	C	5300	Short on A. Plate Volts=Low
399A	1.1	BX-6230-0	0.5	---	P4	D	1100	Short on A. Plate Volts=Low
400A	1.1	BX-6234-0	2.0	---	P4	D	700	Grid No. 3. Short on 3 Plate Volts = Low
400A	1.1	BX-4326-0	5.0	---	P4	D	1400	Osc. Grid. Short on A. Plate Volts=Low
401A/5590	6.3	ET-1567-0	1.6	---	P4	D	2000	Plate Volts=Low
403A/6AK5	6.3	ET-1562-0	1.8	---	P4	C	3150	
403B/5591	6.3	ET-1562-0	1.8	---	P4	C	3150	
404A/5847	6.3	DZ-1684-0	1.7	---	P4	B	12500	

407A	20.0	KV-7608-2	2.0	---	P4	C	3150	Triode No. 1
407A	20.0	BV-3402-8	2.0	---	P4	C	3150	Triode No. 2
408A	20.0	ET-1562-0	1.8	---	P4	C	3150	
409A/6AS6	6.3	ET-1562-7	1.8	---	P4	D	2200	
412A	6.3	EV-0907-3	0.0	88	P3	G	☆	Plate No. 1
412A	6.3	EV-0103-7	0.0	88	P3	G	☆	Plate No. 2
417A/5842	6.3	DZ-5106-0	1.2	---	P4	B	24,000	
420A/5755	12.6	EV-6807-3	0.0	---	P4	D	1550	Triode No. 1
420A/5755	12.6	EV-3102-6	0.0	---	P4	D	1550	Triode No. 2
421A/5998	6.3	HY-4506-2	21.0	---	P4	C	8000	Triode No. 1
421A/5998	6.3	HY-1203-5	21.0	---	P4	C	8000	Triode No. 2
422A	5.0	JS-0600-0	0.0	88	P3	G	☆	Plate No. 1
422A	5.0	JS-0400-0	0.0	88	P3	G	☆	Short on A Plate No. 2 Short on A
713A	6.3	HS-4863-1	1.8	---	P4	D	3000	
717A	6.3	HS-4863-1	1.8	---	P4	D	3000	

3-9-56
mrs

This Document Provided Free

At

www.StevenJohnson.com

NOT FOR RESALE